

**DVCPRO HD AJ-HDX900P (NTSC)**  
**System settings with Apple Final Cut Pro 5.1.1**

---

**Confirmed system**

Power Mac G5 : Dual 2.7GHz, 4GB memory, Mac OS X 10.4.6,  
 QuickTime7.1.1 Final Cut Pro 5.1.1

\* Controlling AJ-HDX900 by FinalCutPro is not possible.

\* Inputting and recording signal from 1394 terminal on AJ-HDX900 is not possible. Print to Video or Export to Tape functions on FinalCutPro are not able to be used with AJ-HDX900.

---

**AJ-HDX900 switch**

TCG

**Position**

R-RUN

**AJ-HDX900 menu**

UB MODE

**Setting**

USER

VITC UB MODE

FRM RATE

FRAME RATE UB

FRAME RATE

**AJ-HDX900 menu**

SYSTEM MODE

CAMERA MODE

**FinalCutPro 5.1.1**

Easy Setup

1080 - 59.94i

60i

DVCPRO HD - 1080i60

30P

DVCPRO HD - 1080i60

24P

DVCPRO HD - 1080i60  
(\*1)

24PA

DVCPRO HD - 1080i60  
(\*2)

720 - 59.94P

60P

DVCPRO HD - 720p60

30P

DVCPRO HD - 720p30

24P

DVCPRO HD - 720p24

1080i - 50i

50i

DVCPRO HD - 1080i50

25P

DVCPRO HD - 1080i50

720 - 50P

50P

(N/A)

25P

(N/A)

N/A means project not applicable

(\*1) as 2:3 pull-down footage

(\*2) as 2:3:3:2 pull-down footage